

(12) **United States Patent**
Iucolano et al.

(10) **Patent No.:** **US 11,101,363 B2**
(45) **Date of Patent:** **Aug. 24, 2021**

(54) **HEMT TRANSISTOR OF THE NORMALLY OFF TYPE INCLUDING A TRENCH CONTAINING A GATE REGION AND FORMING AT LEAST ONE STEP, AND CORRESPONDING MANUFACTURING METHOD**

(58) **Field of Classification Search**
CPC H01L 29/2003; H01L 29/205; H01L 29/4236; H01L 29/4237; H01L 29/66462; H01L 29/7786; H01L 29/7787
See application file for complete search history.

(71) Applicant: **STMICROELECTRONICS S.R.L.**,
Agrate Brianza (IT)

(72) Inventors: **Ferdinando Iucolano**, Gravina di
Catania (IT); **Alfonso Patti**, Tremestieri
Etneo (IT); **Alessandro Chini**, Modena
(IT)

(56) **References Cited**
U.S. PATENT DOCUMENTS
5,021,857 A 6/1991 Suehiro
6,492,669 B2 12/2002 Nakayama et al.
(Continued)

(73) Assignee: **STMICROELECTRONICS S.R.L.**,
Agrate Brianza (IT)

FOREIGN PATENT DOCUMENTS
WO 2014/167825 A1 10/2014

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

OTHER PUBLICATIONS
Cai et al., "Control of Threshold Voltage of AlGaIn/GaN HEMTs by Fluoride-Based Plasma Treatment: From Depletion Mode to Enhancement Mode," *IEEE Transactions on Electron Devices* 53(9):2207-2215, 2006.

(21) Appl. No.: **16/690,035**

(22) Filed: **Nov. 20, 2019**

(Continued)

(65) **Prior Publication Data**
US 2020/0091313 A1 Mar. 19, 2020

Primary Examiner — Jay C Kim
(74) *Attorney, Agent, or Firm* — Seed IP Law Group LLP

Related U.S. Application Data
(62) Division of application No. 15/159,045, filed on May 19, 2016, now Pat. No. 10,522,646.


(30) **Foreign Application Priority Data**
Nov. 12, 2015 (IT) 102015000072111

(57) **ABSTRACT**
A method forms an HEMT transistor of the normally off type, including: a semiconductor heterostructure, which comprises at least one first layer and one second layer, the second layer being set on top of the first layer; a trench, which extends through the second layer and a portion of the first layer; a gate region of conductive material, which extends in the trench; and a dielectric region, which extends in the trench, coats the gate region, and contacts the semiconductor heterostructure. A part of the trench is delimited laterally by a lateral structure that forms at least one first step. The semiconductor heterostructure forms a first edge and a second edge of the first step, the first edge being formed by the first layer.

(51) **Int. Cl.**
H01L 29/15 (2006.01)
H01L 29/66 (2006.01)
(Continued)

(52) **U.S. Cl.**
CPC **H01L 29/66462** (2013.01); **H01L 29/205** (2013.01); **H01L 29/4236** (2013.01);
(Continued)

14 Claims, 6 Drawing Sheets



- (51) **Int. Cl.**
H01L 29/423 (2006.01)
H01L 29/778 (2006.01)
H01L 29/205 (2006.01)
H01L 29/20 (2006.01)
- (52) **U.S. Cl.**
CPC **H01L 29/42376** (2013.01); **H01L 29/7786**
(2013.01); **H01L 29/7787** (2013.01); **H01L**
29/2003 (2013.01)
- (56) **References Cited**
- U.S. PATENT DOCUMENTS
- | | | | | | | | |
|-----------|-----|---------|--|--------------|-----|---------|--------------------------------|
| 6,849,882 | B2 | 2/2005 | Chavarkar et al. | 9,559,183 | B2 | 1/2017 | Inoue et al. |
| 7,470,941 | B2 | 12/2008 | Micovic et al. | 9,590,071 | B2 | 3/2017 | Masumoto |
| 7,605,017 | B2 | 10/2009 | Hayashi et al. | 9,812,532 | B1 | 11/2017 | Chu et al. |
| 7,800,116 | B2 | 9/2010 | Murata et al. | 9,837,521 | B2* | 12/2017 | Yamamoto H01L 21/02255 |
| 7,838,904 | B2 | 11/2010 | Nakazawa et al. | 10,043,897 | B2 | 8/2018 | Ozaki |
| 7,875,907 | B2 | 1/2011 | Honea et al. | 2002/0017648 | A1 | 2/2002 | Kasahara et al. |
| 7,898,004 | B2 | 3/2011 | Wu et al. | 2009/0039421 | A1 | 2/2009 | Otake |
| 7,960,782 | B2 | 6/2011 | Otake | 2010/0301393 | A1 | 12/2010 | Teraguchi |
| 7,985,986 | B2 | 7/2011 | Heikman et al. | 2011/0057257 | A1 | 3/2011 | Park et al. |
| 8,072,002 | B2 | 12/2011 | Niyama et al. | 2011/0133205 | A1 | 6/2011 | Nagahisa et al. |
| 8,133,776 | B2 | 3/2012 | Matsushita | 2013/0056746 | A1 | 3/2013 | Joshin |
| 8,198,178 | B2 | 6/2012 | Heikman et al. | 2013/0105812 | A1 | 5/2013 | Ishigaki et al. |
| 8,278,688 | B2 | 10/2012 | Ohki et al. | 2013/0313612 | A1 | 11/2013 | Khalil et al. |
| 8,338,861 | B2* | 12/2012 | Briere H01L 21/28264
257/194 | 2014/0051221 | A1 | 2/2014 | Khalil et al. |
| 8,390,000 | B2 | 3/2013 | Chu et al. | 2016/0043209 | A1 | 2/2016 | Oyama |
| 8,476,125 | B2 | 7/2013 | Khan et al. | 2016/0197203 | A1* | 7/2016 | Hu H01L 29/872
257/76 |
| 8,525,227 | B2 | 9/2013 | Jeon et al. | | | | |
| 8,541,815 | B2 | 9/2013 | Takemae et al. | | | | |
| 8,587,031 | B2 | 11/2013 | Lu et al. | | | | |
| 8,653,559 | B2 | 2/2014 | Corrion et al. | | | | |
| 8,698,162 | B2 | 4/2014 | Lee et al. | | | | |
| 8,710,550 | B2* | 4/2014 | Ishigaki H01L 29/4236
257/192 | | | | |
| 8,722,474 | B2 | 5/2014 | Yoon et al. | | | | |
| 8,742,460 | B2 | 6/2014 | Mishra et al. | | | | |
| 8,772,842 | B2 | 7/2014 | Dora | | | | |
| 8,772,901 | B2 | 7/2014 | Zhu et al. | | | | |
| 8,803,246 | B2 | 8/2014 | Wu et al. | | | | |
| 8,815,665 | B2 | 8/2014 | Lee et al. | | | | |
| 8,816,395 | B2 | 8/2014 | Bunin et al. | | | | |
| 8,860,089 | B2 | 10/2014 | Park et al. | | | | |
| 8,901,604 | B2 | 12/2014 | Mishra et al. | | | | |
| 8,921,894 | B2 | 12/2014 | Ando et al. | | | | |
| 8,941,118 | B1 | 1/2015 | Chu et al. | | | | |
| 9,024,357 | B2 | 5/2015 | Puglisi et al. | | | | |
| 9,087,718 | B2 | 7/2015 | Lal | | | | |
| 9,087,776 | B2* | 7/2015 | Lee H01L 29/267 | | | | |
| 9,093,366 | B2 | 7/2015 | Mishra et al. | | | | |
| 9,129,888 | B2 | 9/2015 | Lee et al. | | | | |
| 9,166,048 | B2 | 10/2015 | Simin et al. | | | | |
| 9,171,730 | B2 | 10/2015 | Chowdhury et al. | | | | |
| 9,257,513 | B1 | 2/2016 | Liu | | | | |
| 9,263,533 | B2 | 2/2016 | Simin et al. | | | | |
| 9,263,567 | B2 | 2/2016 | Takeya | | | | |
| 9,293,573 | B2 | 3/2016 | Akutsu et al. | | | | |
| 9,306,049 | B2 | 4/2016 | Lee et al. | | | | |
| 9,443,938 | B2 | 9/2016 | Mishra et al. | | | | |
| 9,508,842 | B2 | 11/2016 | Miyake et al. | | | | |
| 9,525,052 | B2 | 12/2016 | Briere | | | | |
| 9,553,152 | B2 | 1/2017 | Ohki et al. | | | | |
- OTHER PUBLICATIONS
- Ghaffari et al., "Operational improvement of AlGaIn/GaN HEMT on SiC substrate with the amended depletion region," *Physica E* 74:303-309, 2015.
- Huang et al., "Evaluation and Application of 600V GaN HEMT in Cascode Structure," *28th Annual IEEE Applied Power Electronics Conference and Exposition*, Long Beach, CA, USA, Mar. 17-21, 2013, pp. 1279-1286.
- Iucolano et al., "Influence of properties of Si₃N₄ passivation layer on the electrical characteristics of Normally-off AlGaIn/GaN HEMT," *1st IEEE Workshop on Wide Bandgap Power Devices and Applications*, Columbus, OH, USA, Oct. 27-29, 2013, pp. 162-165.
- Lanford et al., "Recessed-gate enhancement-mode GaN HEMT with high threshold voltage," *Electronics Letters* 41(7):449-450, 2005.
- Marcon et al., "200 nm GaN-on-Si epitaxy and e-mode device technology," *IEDM15-414*, 2015.
- Ohmaki et al., "Enhancement-Mode, AlGaIn/AlN/GaN High Electron Mobility Transistor with Low On-State Resistance and High Breakdown Voltage," *Japanese Journal of Applied Physics* 45(44):L1168-L1170, 2006. (4 pages).
- Orouji et al., "Novel attributes of AlGaIn/AlN/GaN/SiC HEMTs with the multiple indented channel," *Physica E* 74:407-413, 2015.
- Saito et al., "Recessed-Gate Structure Approach Toward Normally Off High-Voltage AlGaIn/GaN HEMT for Power Electronics Applications," *IEEE Transactions on Electron Devices* 53(2):356-362, 2006.
- Tajima et al., "Effects of Surface Oxidation of AlGaIn on DC Characteristics of AlGaIn/GaN High-Electron-Mobility Transistors," *Japanese Journal of Applied Physics* 48:020203, 2009. (4 pages).
- Uemoto et al., "Gate Injection Transistor (GIT)—A Normally-Off AlGaIn/GaN Power Transistor Using Conductivity Modulation," *IEEE Transactions on Electron Devices* 54(12):3393-3399, 2007.
- Wang et al., "Off-State Breakdown Characterization in AlGaIn/GaN HEMT Using Drain Injection Technique," *IEEE Transactions on Electron Devices* 57(7): 1492-1496, 2010.
- Yue Hao et al., "Nitride Wide Bandgap Semiconductor Materials and Electronic Devices," Beijing: Science Press, Jan. 2013, pp. 109-112 and 273-277 (with corresponding sections of 2016 English language edition).
- * cited by examiner




Fig.3




Fig.4




Fig. 7




Fig. 8




Fig. 9




Fig. 10




Fig. 11




Fig. 12




Fig. 13




Fig. 14




Fig. 15

1

HEMT TRANSISTOR OF THE NORMALLY OFF TYPE INCLUDING A TRENCH CONTAINING A GATE REGION AND FORMING AT LEAST ONE STEP, AND CORRESPONDING MANUFACTURING METHOD

BACKGROUND

Technical Field

The present disclosure relates to a high-electron-mobility transistor (HEMT) of the normally off type including a trench, which comprises a gate region and forms at least one step; further, the present disclosure regards the corresponding manufacturing method.

Description of the Related Art

As is known, HEMT transistors, which are also known as “heterostructure field-effect transistors” (HFETs), are encountering wide diffusion, since they are characterized by the possibility of operating at high frequencies, as well as on account of their high breakdown voltages.

For instance, HEMT transistors are known that include AlGaIn/GaN heterostructures, which, however, are devices of a normally on type, i.e., such that, in the absence of voltage on the respective gate terminals, there in any case occurs passage of current; equivalently, these transistors are said to operate in depletion mode. Since it is generally preferable to provide transistors of the normally off type (equivalently, operating in enrichment mode), numerous variants have been proposed, such as for example the transistor described in U.S. Pat. No. 8,587,031.

In detail, U.S. Pat. No. 8,587,031 describes a transistor including a heterostructure of a layer of aluminum gallium nitride (AlGaIn) and by a layer of gallium nitride (GaN), arranged in contact with one another. Further, the transistor has a first gate region, which is arranged within a recess that extends in the AlGaIn layer and enables modulation of a channel of the normally off type.

Today, there are thus available HEMT transistors operating in enrichment mode. However, these solutions are in any case affected by the so-called phenomenon of drain-induced barrier lowering (DIBL), also known as “early-breakdown phenomenon”.

Unlike breakdown, the DIBL phenomenon occurs for low drain-to-source voltages (typically, for voltages comprised between 10 V and 30 V) and entails, in the presence of a zero voltage between gate and source, a sudden increase of the current that circulates between the drain and the source. In greater detail, denoting the voltages present between i) the gate and the source and between ii) the drain and the source as the voltages V_{gs} and V_{ds} , respectively, and the current that circulates between the drain and the source when $V_{gs}=0$ as the leakage current, when $V_{ds}<V_{dibl}$ (where V_{dibl} is the voltage at which the DIBL phenomenon occurs) the leakage current density is typically of the order of nanoamps per millimeter. Instead, if $V_{gs}=0$ and V_{ds} exceeds V_{dibl} , the leakage current density may even be of the order of the microamps per millimeter. Since the DIBL phenomenon causes premature turning-on of the transistor, there is felt the need to prevent onset of this phenomenon, or in any case reduce the effects thereof.

BRIEF SUMMARY

At least some embodiments of the present disclosure provide a HEMT transistor that will overcome at least in part the drawbacks of the known art.

2

According to the present disclosure a HEMT transistor includes:

a semiconductor heterostructure including a first semiconductor layer and a second semiconductor layer, the second semiconductor layer being arranged on top of the first layer;

a trench which extends through the second semiconductor layer and a portion of the first semiconductor layer;

a gate region of conductive material, which extends in the trench; and

a dielectric region which extends in the trench, coats the gate region, and contacts the semiconductor Heterostructure.

A part of the trench is delimited laterally by a lateral structure that forms a first step and the semiconductor heterostructure forms a first edge and a second edge of said first step, the first edge being formed by the first semiconductor layer.

At least some embodiments of the present disclosure provide a method for manufacturing a HEMT transistor that includes:

in a semiconductor heterostructure that includes a first semiconductor layer and a second semiconductor layer arranged on top of the first semiconductor layer, forming a trench that extends through the second semiconductor layer and a portion of the first semiconductor layer;

forming a gate region of conductive material within the trench;

within the trench, forming a dielectric region that coats the gate region and contacts the semiconductor heterostructure; and

forming a lateral structure that delimits laterally a part of the trench and forms a first step; and wherein the semiconductor heterostructure forms a first edge and a second edge of said first step, the first edge being formed by the first semiconductor layer.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

For a better understanding of the present disclosure, preferred embodiments thereof are now described, purely by way of non-limiting example and with reference to the attached drawings, wherein:

FIG. 1 is a schematic illustration of a cross-section (not in scale) of a portion of the present HEMT transistor;

FIG. 2 is a schematic perspective view (not in scale) of a trench of the HEMT transistor shown in FIG. 1;

FIG. 3 is a schematic illustration of a cross-section (not in scale) of a portion of the HEMT transistor shown in FIG. 1;

FIG. 4 shows two examples of plots, as a function of the drain-to-source voltage, of the leakage current, for a HEMT transistor of a known type and the present HEMT transistor, respectively;

FIG. 5 shows two examples of plots of the electrical field versus the drain voltage, for a HEMT transistor of a known type and for the present HEMT transistor, respectively;

FIGS. 6-8 and 15 are schematic cross-sectional views (not in scale) of further embodiments of the present HEMT transistor;

FIGS. 9-14 are schematic cross-sectional views (not in scale) of the HEMT transistor illustrated in FIG. 1, during successive steps of a manufacturing method.

DETAILED DESCRIPTION

FIG. 1 shows a first embodiment of the present HEMT transistor, designated by 1.

In detail, the HEMT transistor **1** comprises a semiconductor body **2**, which in turn comprises a first layer **4** and a second layer **6**, referred to hereinafter as the bottom layer **4** and the top layer **6**, respectively.

The bottom layer **4** is of a first semiconductor material, such as for example a first semiconductor alloy of elements of Groups III and V of the Periodic Table; purely by way of example, in what follows it is assumed that the bottom layer **4** is of gallium nitride (GaN).

The top layer **6** overlies the bottom layer **4**, with which it is in direct contact, and is of a second semiconductor material, such as for example a second semiconductor alloy of elements of Groups III-V of the Periodic Table, this second semiconductor alloy being different from the first semiconductor alloy. Purely by way of example, in what follows it is assumed that the top layer **6** is of aluminum gallium nitride (AlGaN).

The bottom layer **4** and the top layer **6** are, for example, of an N type. Furthermore, the bottom layer **4** has a thickness of, for example, between 20 nm and 7 μm , while the top layer **6** has a thickness of, for example, between 5 nm and 400 nm.

Although not shown, the semiconductor body **2** further comprises a substrate, made for example of silicon, on which the bottom layer **4** is formed. Since this substrate is irrelevant for the purposes of the present disclosure, it will not be mentioned any further in the present description.

The HEMT transistor **1** further comprises a passivation region **8**, which overlies, in direct contact, the top layer **6** and is made, for example, of silicon nitride. For instance, the passivation region **8** has a thickness of 100 nm. The passivation region **8** forms a first surface S_a of the HEMT transistor **1**.

The HEMT transistor **1** further comprises a gate region **10**, which extends inside a trench **15** and is of conductive material; for example, the gate region **10** may be made up of one or more metal layers, made for example of aluminum, nickel, or tungsten.

In detail, the trench **15** extends through the passivation region **8**, starting from the first surface S_a , as well as through the top layer **6**. Furthermore, the trench **15** traverses a top portion of the bottom layer **4**, arranged in contact with the top layer **6**.

In greater detail, the trench **15** is delimited by a first side wall P_{11} , a second side wall P_{12} , a third side wall P_{13} , and a fourth side wall P_{14} , which are mutually parallel and are perpendicular to the first surface S_a . Further, the trench **15** is delimited by a first bottom wall P_{b1} , a second bottom wall P_{b2} , and a third bottom wall P_{b3} , which are parallel to one another and to the first surface S_a .

In particular, the first bottom wall P_{b1} extends in the bottom layer **4**, to a first depth (measured, for example, with respect to the first surface S_a). Also the second bottom wall P_{b2} and the third bottom wall P_{b3} extend in the bottom layer **4**, to the same depth, which is less than the aforementioned first depth. Furthermore, the first side wall P_{11} connects the first and second bottom walls P_{b1} , P_{b2} ; the third side wall P_{13} connects, instead, the first and third bottom walls P_{b1} , P_{b3} . Furthermore, the second side wall P_{12} connects the second bottom wall P_{b2} to the first surface S_a ; the fourth side wall P_{14} connects the third bottom wall P_{b3} to the first surface S_a .

In practice, as shown in greater detail in FIG. 2, the first bottom wall P_{b1} and the first side wall P_{11} form a first edge E_1 ; further, the first side wall P_{11} and the second bottom wall P_{b2} form a second edge E_2 , which is parallel to the first edge E_1 , with which it is coplanar. In addition, the second bottom wall P_{b2} and the second side wall P_{12} form a third edge E_3 ,

which is parallel to the second edge E_2 , with which it is coplanar. In turn, the second side wall P_{12} forms a fourth edge E_4 with the first surface S_a (not shown in FIG. 2).

In addition, the first bottom wall P_{b1} and the third side wall P_{13} form a fifth edge E_5 ; further, the third side wall P_{13} and the third bottom wall P_{b3} form a sixth edge E_6 , which is parallel to the fifth edge E_5 , with which it is coplanar. In addition, the third bottom wall P_{b3} and the fourth side wall P_{14} form a seventh edge E_7 , which is parallel to the sixth edge E_6 , with which it is coplanar. In turn, the fourth side wall P_{14} forms an eighth edge E_8 with the first surface S_a .

In even greater detail, the first and third side walls P_{11} , P_{13} are set apart from one another by a distance equal to L_1 (measured in a direction perpendicular to the first and third side walls P_{11} , P_{13}), which thus represents the width of the first bottom wall P_{b1} . The widths of the second and third bottom walls P_{b2} , P_{b3} are instead designated, respectively, by L_2 and L_3 . In addition, the first and third side walls P_{11} , P_{13} have a height equal to H_1 , measured in a direction perpendicular to the first bottom wall P_{b1} . Furthermore, as shown in FIG. 1, each one of the second and fourth side walls P_{12} , P_{14} has a respective bottom portion, which extends starting, respectively, from the third and seventh edges E_3 , E_7 until it contacts the top layer **6**, this portion having a height H_2 .

In practice, the trench **15** forms a first cavity **22** and a second cavity **24**, communicating with one another and having the same length. The first cavity **22** gives out onto the first surface S_a , overlies the second cavity **24** and has a width equal to $L_1+L_2+L_3$; the second cavity **24** has a width equal to L_1 . Purely by way of example, each of the widths L_1 , L_2 and L_3 may be comprised between 0.1 μm and 10 μm ; further, the height H_1 may, for example, be comprised between 1 nm and 500 nm, whereas the height H_2 may, for example, be comprised between 0 and 500 nm.

In other words, the first side wall P_{11} and the second bottom wall P_{b2} form a first step, i.e., a first shoulder, of a lateral structure LS that delimits the trench **15** laterally and extends from a side of the first bottom surface P_{b1} . In particular, denoting the ensemble of the semiconductor body **2** and of the passivation region **8** as the main body, the lateral structure LS is formed by the main body. Furthermore, the second bottom wall P_{b2} , the second side wall P_{12} , and the first surface S_a form a sort of second step of the aforementioned lateral structure LS. The first and second steps are arranged in succession, in such a way that the lateral structure LS assumes a staircase profile.

The HEMT transistor **1** further comprises a dielectric region **18**, which is formed, for example, by aluminum nitride (AlN), or silicon nitride (SiN), or silicon oxide (SiO_2), and coats the first surface S_a . Furthermore, the dielectric region **18** internally coats the trench **15**, i.e., coats, among others, the first, second, and third bottom walls P_{b1} , P_{b2} , P_{b3} , as well as the first, second, third, and fourth side walls P_{11} , P_{12} , P_{13} and P_{14} . In this connection, as previously mentioned, the first, second, and third bottom walls P_{b1} , P_{b2} , P_{b3} are formed by the bottom layer **4**, as also the first and third side walls P_{11} , P_{13} , while each of the second and fourth side walls P_{12} , P_{14} is formed by the bottom layer **4**, the top layer **6**, and the passivation region **8**.

In greater detail, the gate region **10** comprises a bottom portion **11a**, arranged within the second cavity **24**, and a central portion **11b**, arranged within the first cavity **22**, on the bottom portion **11a**, with which it is in direct contact. The dielectric region **18** surrounds the bottom portion **11a** and the central portion **11b** of the gate region **10**, which are thus arranged in the trench **15** more internally than the

dielectric region **18** and are coated by the latter. In particular, the dielectric region **18** insulates the bottom portion **11a** and the central portion **11b** of the gate region **10** from the semiconductor body **2**, as well as from the passivation region **8**.

In even greater detail, the bottom portion **11a** and the central portion **11b** of the gate region **10** are both parallelepipedal in shape and have a width D_1 and a width D_2 , respectively, with $D_1 < L_1$ and $D_2 > L_1$. Furthermore, without any loss of generality, the bottom portion **11a** extends to a depth W_{11a} (measured starting from the first surface S_a), greater than the maximum depth to which the top layer **6** (designated by W_6) extends; the central portion **11b** extends, instead, to a depth $W_{11b} < W_{11a}$. Without any loss of generality, in the embodiment shown in FIG. **1** we have $W_6 < W_{11b}$.

In other words, as shown in greater detail in FIG. **3**, the gate region **10** is delimited at the bottom by a first horizontal wall O_1 , a second horizontal wall O_2 , and a third horizontal wall O_3 and by a first vertical wall V_1 and a second vertical wall V_2 . In particular, the first horizontal wall O_1 delimits, at the bottom, the bottom portion **11a** of the gate region **10**, which is delimited laterally by the first and second vertical walls V_1, V_2 . The central portion **11b** of the gate region **10** is delimited, at the bottom (in part), by the second and third horizontal walls O_2, O_3 . The first vertical wall V_1 connects the first and second horizontal walls O_1, O_2 , with which it forms a corresponding step of the gate region **10**. Likewise, the second vertical wall V_2 connects the first and third horizontal walls O_1, O_3 , with which it forms a corresponding step of the gate region **10**. Furthermore, the first horizontal wall O_1 and the first vertical wall V_1 form a first edge G_1 of the gate region **10**, parallel to the first edge E_1 of the trench **15**, while the first vertical wall V_1 and the second horizontal wall O_2 form a second edge G_2 of the gate region **10**, parallel to the second edge E_2 of the trench **15**.

As shown again in FIG. **3**, the gate region **10** further comprises a top portion **11c**, which extends on the central portion **11b**, with which it is in direct contact. Furthermore, the central portion **11b** of the gate region **10** is delimited laterally by a third vertical wall V_3 and a fourth vertical wall V_4 , which are parallel to one another and face, respectively, the second and fourth side walls P_{12}, P_{14} of the trench **15**. The third vertical wall V_3 forms a third edge G_3 and a fourth edge G_4 of the gate region **10** with the second horizontal wall O_2 and the top portion **11c** of the gate region **10**, respectively.

In practice, to a first approximation, the dielectric region **18** has an approximately constant thickness inside the trench **15**; i.e., it forms a sort of conformal layer that coats the walls of the trench **15**; consequently, the part of gate region **10** contained within the trench **15** is delimited by a surface that follows the profile of the trench **15** (and thus of the lateral structure LS). Consequently, corresponding to each edge/step of the trench **15** is an edge/step of the part of gate region **10** contained within the trench **15**.

Again with reference to FIG. **1**, the portion of dielectric region **18** that extends on the first surface S_a is delimited at the top by a second surface S_b , substantially parallel to the first surface S_a . Furthermore, the top portion **11c** of the gate region **10** has a width greater than $L_1 + L_2 + L_3$ and projects laterally both with respect to the second side wall P_{12} and with respect to the fourth side wall P_{14} . Without any loss of generality, in the embodiment shown in FIG. **1**, the top portion **11c** of the gate region **10** projects laterally from the second side wall P_{12} to a greater extent than the top portion **11c** projects from the fourth side wall P_{14} .

The HEMT transistor **1** further comprises a source metallization **26** and a drain metallization **28**, arranged on sides

opposite to the trench **15** and to the top portion **11c** of the gate region **10**. Each one of the source metallization **26** and the drain metallization **28** traverses the portion of dielectric region **18** arranged on top of the front surface S_a and the portion underlying the passivation region **8** until it contacts the top layer **6**. In a per se known manner, each one of the source metallization **26** and the drain metallization **28** may be formed, for example, by a corresponding plurality of metal layers (for example, of titanium, aluminum, and tungsten); further, a top portion of each one of the source metallization **26** and the drain metallization **28** extends up to a height greater than the height of the second surface S_b .

In greater detail, the second and fourth side walls P_{12}, P_{14} of the trench **15** face the drain metallization **28** and the source metallization **26**, respectively.

In use, the gate region **10**, the dielectric region **18**, and the bottom layer **4** form a MOSFET, the channel of which extends in the bottom layer **4**, underneath the first bottom wall P_{b1} . This channel, of the normally off type, may be modulated by applying a voltage to the gate region **10**.

In a per se known manner, underneath the interface between the bottom layer **4** and the top layer **6**, thus in the bottom layer **4**, a so-called "two-dimensional electron gas" (2DEG) is formed, which represents the channel (of the normally on type) of the HEMT transistor **1**. Also this channel is modulated by the voltage present on the gate region **10**, thanks to the presence, in the top portion **11c** of the gate region **10**, of a projection that extends, with respect to the underlying central portion **11b**, towards the drain metallization **28**, thus overlying a corresponding portion of the two-dimensional electron gas. In other words, the top layer **6** functions as barrier layer, whereas the bottom layer **4** functions as buffer layer.

The HEMT transistor **1** has thus, as a whole, a channel of the normally off type, thanks to the presence of the aforementioned MOSFET. Furthermore, it may be shown that the HEMT transistor **1** exhibits a leakage current of the type illustrated in FIG. **4**, where there further appears an example of leakage current of a HEMT transistor of a known type.

In practice, the HEMT transistor **1** is not affected by the DIBL phenomenon. This is due to the fact that, thanks to the presence of the aforementioned first step of the trench **15**, the electrical field at the aforementioned first edge E_1 presents a pattern as a function of the drain voltage that is of the type shown in FIG. **5** (on the hypothesis of zero gate and source voltages), which further represents an example of the corresponding plot of the electrical field that arises in a HEMT transistor of a known type and where the gate region is formed in a recess of a traditional shape, at a bottom edge of this recess. In fact, the presence of the aforementioned first step of the lateral structure implies the presence, in the semiconductor body **2**, of the third edge E_3 ; consequently, the electrical field is approximately shared between the first and third edges E_1, E_3 .

Further possible are embodiments of the type shown in FIG. **1**, but where the trench **15** extends to depths different from what has been described previously. For instance, as shown in FIG. **6**, it is possible for the first bottom wall P_{b1} of the trench **15** to lie in the plane of the interface between the bottom layer **4** and the top layer **6**. In this case, the gate region **10** is entirely on top of the bottom layer **4**. Consequently, the second edge E_2 of the trench **15** and the aforementioned first step of the trench **15** are formed by the top layer **6**. The first edge E_1 is instead still in contact with the bottom layer **4**, and thus guarantees the aforementioned reduction of the electrical field.

According to a different embodiment, shown in FIG. 7, the HEMT transistor **1** is of the same type as the one shown in FIG. 1, apart from the fact that the second edge E_2 of the trench **15** is formed by the top layer **6**. Without any loss of generality, assuming that the passivation region **8** extends to a depth W_s , we have $W_{11b} > W_8$ even though variations where we have $W_{11b} = W_8$ are in any case possible.

In general, the embodiments shown in FIGS. 6 and 7 are characterized by low resistances between the source metallization **26** and drain metallization **28**, since in both cases a part of the channel of the MOSFET is formed in the top layer **6**; the consequent greater extension of the two-dimensional gas thus entails a reduction of the so-called R_{ON} .

FIG. 8 shows, instead, a further embodiment in which the lateral structure LS comprises more than two steps. For instance, without any loss of generality, in the embodiment shown in FIG. 8 the lateral structure LS forms, in addition to the aforementioned first and second steps (the upper edges of which E_2 , E_4 are shown in FIG. 8), a further three steps, the upper edges of which are designated by E_{x1} , E_{x2} , and E_{x3} , respectively. Purely by way of example, the edges E_{x1} , E_{x2} , and E_{x3} are formed by the top layer **6**. The central portion **11** of the gate region **10** thus forms another three corresponding additional steps, the upper edges of which are designated by G_{x1} , G_{x2} and G_{x3} , respectively; without any loss of generality, in FIG. 8 the edge G_{x3} is set coplanar with the interface between the bottom layer **4** and the top layer **6**.

It may be shown that, as the number of steps of the lateral structure LS increases, the electrical field present between the gate region **10** and the drain metallization **28** is distributed more evenly along the lateral structure LS since the corresponding peaks, located in the presence of the edges, reduce their own amplitude. In this way, any deterioration of the HEMT transistor during the turning off steps, in which the transistor is subjected to high drain voltages, is prevented.

The present HEMT transistor **1** may be produced, for example, by implementing the manufacturing method described in what follows. Without any loss of generality and purely by way of non-limiting example, the manufacturing method is described with reference to production of the HEMT transistor **1** shown in FIG. 1.

Initially, as shown in FIG. 9, the main body, including the semiconductor body **2** and the passivation region **8**, is provided in a per se known manner.

Next, as shown in FIG. 10, in a per se known manner, a photolithographic process and a subsequent etching process are carried out in order to remove selectively a portion of the passivation region **8**, an underlying portion of the top layer **6**, and an underlying portion of the bottom layer **4** for forming a first recess **40**, which has the shape of a parallel-epiped and has a depth greater than the aforementioned depth W_{11b} . The first recess **40** is delimited, at the bottom, by a plane surface SR, formed by the bottom layer **4**, and is designed to house the central portion **11b** of the gate region **10** and the portion of dielectric region **18** that coats it.

Next, as shown in FIG. 11, in a per se known manner a further photolithographic process and a subsequent further etching process are carried out in order to remove selectively a portion of the bottom layer **4**, starting from the plane surface SR. In particular, a portion of the bottom layer **4** that forms a central portion of the plane surface SR is removed, said central portion separating a pair of lateral portions of the plane surface SR, which in turn form the second and third bottom walls P_{b2} , P_{b3} , respectively, of the trench **15**. In this way, a second recess **42** is formed, which is delimited at the bottom by the first bottom wall P_{b1} and has a smaller width

than the first recess **40**. The second recess **42** is further delimited laterally by the first and third side walls P_{11} , P_{13} and is designed to house the bottom portion **11a** of the gate region **10**, and thus extends to a depth greater than the aforementioned depth W_{11a} . The first and second recesses **40**, **42** form the trench **15**.

Next, as shown in FIG. 12, formed on the first surface S_a and within the trench **15** is a dielectric layer **50**, made, for example, of aluminum nitride or silicon nitride. The dielectric layer **50** thus coats the walls of the trench **15** and is formed, for example, by deposition.

Next, as shown in FIG. 13, the source metallization **26** and the drain metallization **28** are formed in a per se known manner. For this purpose, even though not shown in detail, it is possible to carry out a further photolithographic process and a subsequent etching process for removing selectively portions of the dielectric layer **50** and underlying portions of the passivation region **8**, to form cavities designed to house, respectively, the source metallization **26** and the drain metallization **28**, which are subsequently formed within these cavities by the so-called "lift-off" technique. According to the lift-off technique, by photolithography a resist mask is formed, which leaves exposed just the regions of the HEMT transistor **1** that are to be overlaid by the source metallization **26** and by the drain metallization **28**. Next, metal material is deposited on the HEMT transistor **1**; subsequent removal of the resist mask also entails removal of the metal material overlying the resist mask itself. Once the source metallization **26** and the drain metallization **28** are formed, what remains of the dielectric layer **50** forms the dielectric region **18**.

Next, even though not shown, a thermal process is carried out, for example at a temperature comprised between 500° C. and 900° C. for formation of the contacts.

Next, as shown in FIG. 14, the gate region **10** is formed, the bottom and central portions **11a**, **11b** of which extend within the trench **15**. Also the gate region **10** may be formed by a corresponding lift-off process, which envisages forming a corresponding resist mask, depositing conductive material both on the mask and on the portion of HEMT transistor **1** left free from the mask, and subsequently removing the resist mask and the conductive material arranged on top of it.

As regards, instead, embodiments of the type shown in FIG. 8, i.e., embodiments in which the lateral structure LS forms more than two steps, they may be formed for example by carrying out the steps (not shown) of:

a) removing selectively a top portion of the main body for removing a corresponding recess, delimited by a bottom surface;

b) starting from the aforementioned bottom surface, removing selectively an underlying portion of main body for forming a further recess, delimited by a respective bottom surface, the further recess having a width smaller than the previous recess and being laterally staggered with respect to the side walls of the previous recess; and

c) iterating step b) until formation of the desired number of steps.

In the case where the manufacturing method just described above is adopted, the shape of the trench **15** may differ from what is shown in FIG. 8; in particular, the portion of trench **15** facing the source metallization **26** may include a number of steps equal to that of the lateral structure LS.

From what has been described and illustrated previously, the advantages that the present solution affords emerge clearly.

In particular, the present HEMT transistor is substantially immune from the DIBL phenomenon since, in use, the electrical field at the first edge E_1 (in contact with the first layer **4**) is reduced, thanks to the presence in the semiconductor body **2** of at least the third edge E_3 .

In conclusion, it is clear that modifications and variations may be made to what has been described and illustrated so far, without thereby departing from the scope of the present disclosure.

For instance, each one of the source metallization **26** and the drain metallization **28** may penetrate in part within the top layer **6**, as well as possibly also in a top portion of the bottom layer **4**.

The bottom layer **4** may include a respective top portion and a respective bottom portion (not shown), which are doped for example with carbon atoms; in this case, the top portion is doped with carbon atoms to an extent smaller than the bottom portion and functions as so-called channel layer, whereas the bottom portion of the bottom layer **4** functions as buffer layer. In this case, if the second and third bottom walls P_{b2} , P_{b3} are formed by the bottom layer **4**, they may be formed indifferently by the top portion or by the bottom portion of the bottom layer **4**.

Doping of the semiconductor body **2** may be of a type different from what has been described. For instance, the bottom layer **4** and the top layer **6** may be of a P type.

As regards the trench **15**, the portion of trench **15** arranged between the first bottom wall P_{b1} and the source metallization **26** may have a shape different from what has been described. For instance, embodiments are possible of the type shown in FIG. **1** but where the third bottom wall P_{b3} is absent, in which case the third and fourth side walls P_{t3} , P_{t4} are replaced by a single side wall. In this connection, it may be noted how, for the purposes of prevention of the DIBL phenomenon, the shape of the further lateral structure that delimits the trench **15** laterally and is opposite to the lateral structure LS is to a first approximation irrelevant since the electrical field between the source metallization **26** and the gate region **10** is less intense than the electrical field present between the gate region **10** and the drain metallization **28**.

The passivation region **18** may be absent, in which case the first surface S_a is formed by the top layer **6**.

Again, as shown in FIG. **15**, between the bottom layer **4** and the top layer **6** there may be present a spacer layer **200**, made, for example, of aluminum nitride and having a smaller thickness, for example of 1 nm; the spacer layer **200** has the purpose of improving the mobility of the two-dimensional electron gas. In general, there are thus possible further embodiments that correspond to embodiments described previously but further include the spacer layer **200**. In these further embodiments, the spatial distribution of the steps and of the edges of the lateral structure LS may, for example, correspond to that of the corresponding embodiments described previously in the sense that, if in a previous embodiment an edge of a step is formed by a given layer (for example, the bottom layer **4** or the top layer **6**), in the corresponding further embodiment the corresponding edge is again formed by that given layer.

Once again with reference to the lateral structure LS, even though previously orthogonal steps have been described, i.e., steps that connect pairs of horizontal surfaces by vertical surfaces, it is, however, possible for the vertical surfaces of one or more steps to be transverse with respect to the corresponding horizontal surfaces and/or for one or both of the horizontal surfaces of one or more steps to be replaced by surfaces that are not parallel to the first surface S_a . In

other words, in general the walls and the vertical surfaces may be not perfectly orthogonal to the first surface S_a .

The various embodiments described above can be combined to provide further embodiments. These and other changes can be made to the embodiments in light of the above-detailed description. In general, in the following claims, the terms used should not be construed to limit the claims to the specific embodiments disclosed in the specification and the claims, but should be construed to include all possible embodiments along with the full scope of equivalents to which such claims are entitled. Accordingly, the claims are not limited by the disclosure.

The invention claimed is:

1. A method for manufacturing a normally off heterostructure field-effect transistor (HEMT), comprising:

forming a trench that extends through a portion of a first semiconductor layer of semiconductor heterostructure and through a second semiconductor layer that is on the first semiconductor layer, the trench including a bottom wall of the trench;

forming a first step having first and second walls in the trench by forming a lateral structure that delimits a part of the trench laterally, wherein the first wall extends upwardly from the bottom wall and the second wall extends outwardly from the first wall, wherein forming the lateral structure includes:

forming the lateral structure with a staircase shape;

forming a second step that includes a third wall and a fourth wall, the third wall being part of the semiconductor heterostructure, the fourth wall extending laterally from the third wall; and

forming a third step positioned between the first step and the second step, the third step including a fifth wall extending from the second wall of the first step and a sixth wall extending from the fifth wall to the third wall of the second step;

forming a dielectric layer in the trench on the semiconductor heterostructure and on the bottom wall, and the first and second walls of the first step; and

forming a gate region of conductive material on the first step.

2. The method according to claim **1**, further comprising forming a first electrode region and a second electrode region, the trench being arranged between the first and second electrode regions.

3. The method according to claim **1**, wherein forming the second step includes forming the third wall and the fourth wall in the second semiconductor layer.

4. The method according to claim **1**, wherein forming the gate region includes forming a first portion which is arranged in the trench and includes, on a first side of the first portion, a surface that forms a step of the gate region, said step of the gate region being surrounded by, and physically separated from, the semiconductor heterostructure.

5. The method according to claim **4**, wherein forming the gate region further comprises forming a second portion which extends on the first portion and projects laterally from the trench.

6. The method according to claim **1**, wherein the first and second semiconductor layers are of two materials that are configured to generate a two-dimensional electron gas in the first semiconductor layer.

7. The method according to claim **1**, further comprising forming an insulator on the second semiconductor layer, wherein:

forming the trench includes forming the trench through the insulator; and

11

forming the dielectric layer includes forming an upper portion of the dielectric layer on the insulator such that the insulator is positioned between a bottom surface of the upper portion of the dielectric layer and a top surface of the second semiconductor layer.

8. A method for manufacturing a normally off HEMT transistor, the method comprising:

forming a trench that extends through a portion of a first semiconductor layer of a semiconductor heterostructure and through a second semiconductor layer that is on the first semiconductor layer wherein forming the trench further includes:

forming a first step that includes a first wall and a second wall by forming a lateral structure that delimits laterally a part of the trench, forming the first step includes:

forming a first recess in the semiconductor heterostructure, the first recess having a bottom delimited by a surface of the semiconductor heterostructure; and

subsequently forming a second recess in the semiconductor heterostructure, the second recess having a width smaller than the first recess and being delimited at least in part by the first semiconductor layer;

forming a second step that includes a third wall and a fourth wall, the third wall being formed by the semiconductor heterostructure, the fourth wall extending laterally from the third wall; and

forming a third step positioned between the first step and the second step, the third step including a fifth wall extending from the second wall of the first step and a sixth wall extending from the fifth wall to the third wall of the second step;

forming a gate region of conductive material within the trench; and

forming a dielectric layer between the gate region and the semiconductor heterostructure.

9. The method according to claim **8**, wherein:

forming the dielectric layer includes internally coating the first and second recesses with the dielectric layer; and forming the gate region includes forming the gate region in contact with the dielectric layer.

10. The method according to claim **8**, further comprising forming an insulator on the second semiconductor layer, wherein:

forming the trench includes forming the trench through the insulator; and

forming the dielectric layer includes forming an upper portion of the dielectric layer on the insulator such that the insulator is positioned between a bottom surface of the upper portion of the dielectric layer and a top surface of the second semiconductor layer.

11. A method for manufacturing a normally off HEMT transistor comprising:

forming a trench that extends through a portion of a first semiconductor layer of a semiconductor heterostructure and through a second semiconductor layer that is on the first semiconductor layer, wherein forming the trench further includes:

forming a first step that includes a first wall and a second wall by forming a lateral structure that delimits laterally a part of the trench, forming the first step includes:

forming a first recess in the semiconductor heterostructure, the first recess having a bottom delimited by a surface of the semiconductor heterostructure; and

12

subsequently forming a second recess in the semiconductor heterostructure, the second recess having a width smaller than the first recess and being delimited at least in part by the first semiconductor layer;

forming a second step that includes a third wall and a fourth wall, the third wall being formed by the semiconductor heterostructure, the fourth wall extending laterally from the third wall, wherein forming the lateral structure includes forming the first and second steps on a first side of the trench and forming a planar structure on a second side of the trench opposite the first side, the planar structure having a wall that extends from the first semiconductor layer and completely through the second semiconductor layer, the wall of the planar structure having a first height;

forming a gate region of conductive material within the trench; and

forming a dielectric layer between the gate region and the semiconductor heterostructure;

the first wall is formed by the first semiconductor layer and is parallel to the wall of the planar structure; and the third wall is formed by the second semiconductor layer and is parallel to the wall of the planar structure.

12. The method according to claim **11**, wherein the first wall has a first height, the planar surface has a second height, and the third wall has a third height, the second height being greater than a sum of the first height and the third height.

13. A method for manufacturing normally off heterostructure field-effect transistor (HEMT), the method comprising: in a semiconductor heterostructure including a first semiconductor layer and a second semiconductor layer arranged on top of the first layer, forming a trench that extends through the second semiconductor layer and a portion of the first semiconductor layer;

forming a passivation layer on the second semiconductor layer;

forming a conductive gate region extending in the trench through the passivation layer and the semiconductor heterostructure; and

forming a dielectric region coating the gate region and contacting the semiconductor heterostructure and the passivation layer, wherein forming the trench includes: defining a planar structure on a first side of the trench, the planar structure having a wall that extends from the first semiconductor layer to the passivation layer through the second semiconductor layer; and

defining a stepped structure at a second side of the trench opposite to the first side, the stepped structure including a first and a second step, the first step including a first wall formed by the first semiconductor layer and parallel to the planar structure and a second wall extending laterally from the first wall, the second step including a third wall formed by the second semiconductor layer and parallel to the planar structure and a fourth wall extending laterally from the third wall, wherein forming the first step includes:

forming a first recess in the semiconductor heterostructure, the first recess having a bottom delimited by a surface of the semiconductor heterostructure; and

subsequently forming a second recess in the semiconductor heterostructure, the second recess hav-

13

ing a width smaller than the first recess and being delimited at least in part by the first semiconductor layer.

14. The method according to claim **13**, wherein the first wall has a first height, the planar structure has a second height, and the third wall has a third height, the second height being greater than a sum of the first height and the third height.

* * * * *

14